

NF Series Ballast



Moving parts are a turn-off to some. Again, we have listened. Looking to keep our sealed ballasts as reliable as our fan cooled ballasts, we upgraded the interior components to stand up to higher temperatures. The NF Series is an NCCS ready smart ballast. Like all of our ballasts the NF Series comes with Random Start technology. Random Start uses an algorithm that will start the ballast within a 0-15 second window. This allows for less initial power draw when using multiple ballasts. ETL listed meeting product safety standards.



- NCCS ready smart ballast technology
- Diagnostic LED
- Random Start technology
- Non Fan Ballast (fully sealed)
- Soft Start & Soft Dim for bulb longevity
- Dimmable lamp function: 100%-75%-50%
- Strikes both MH and HPS Bulbs
- Multi-voltage – 120 - 240V
- Comprehensive short-circuit-circuit overheat/lamp failure protection
- 3 Year Warranty

Output Power	Input Voltage	Input Current	Bulb	Dimming Settings	PF	THDI	CF	Weight	Size	Input Frequency
1000W	120-240,	8.1/4.3A	SE	110%, 100%, 75%,50%	>0.99	<10%	<1.7	13	14.5" x 7.0" x 4.2"	50/60